

Conventional Fire Alarm Panel with Auto Dialer



Features

- Inbuilt self testing facility.
- Four Zones with LED and LCD status Display.
- Built in Battery Charger and SMPS Power Supply for stable and durable performance.
- Support all Smoke, Heat and Ionization type sensors.
- Full Reset, Lamp Test and Silence Facility.
- Auto Dialer supports all Telecom Networks with 20sec message record and 10 telephone nos.
- Save built in event record even after power failure.
- CE, FCC & RoHS Certified

Specification

Electrical	
Power Supply	230V AC
Battery Backup	24V DC, 7AH (External)
Battery Charger	Internal, Constant Current
End of line Resistance	4.7 k Ohm
Protection	AC Fuse, DC Fuse, Battery Fuse
Audio – Visual Alarm	AC Fail, DC Fail, Battery Low, Zone Isolation Zone Input Short, Zone Input Open, Zone Isolation
Input	Maximum 25 Sensors in each zone
Output	For Hooter (24V, 2 amp) Aux Relay Change Over Contact
Testing	A Full Featured Testing of All Zone for Simulated Fire, Open and Short
Note:	Product appearance & technical specifications are Subject to change without any prior notice.